

## PST122D

2024/02/28

## Overview

This IC is a 40V withstand voltage 2ch voltage detection IC that is ideal for monitoring the voltage of car batteries.

The voltage detection accuracy is  $\pm 2\%$  including temperature fluctuation, and the output form is Nch open drain output.

The current consumption is 2.7  $\mu\text{A}$  (typ.), And the operating temperature range is  $-40$  to  $105^\circ\text{C}$ .

## Application

- Voltage monitor for car battery
- Voltage monitor for AC / DC converter output voltage

## Features

High withstand voltage, High accuracy detection, Low current consumption, Hysteresis voltage selectable (0.1V to 4.0V)

## Main specifications

Absolute maximum rating [V]	Recommended operating voltage Min. [V]	Recommended operating voltage Max. [V]	Detection voltage Min. [V]	Detection voltage Max. [V]	Detection voltage accuracy [%]	Consumption current [ $\mu\text{A}$ ]
40.0	2.70	20.00	5.0	10.0	$\pm 2$	3.70
Output type	Output Logic	Separated sense pin	Manual reset	Circuit structure		
Open drain	ch1:Active H	Yes	No	2ch Reset		

## PST122D

2024/02/28

open drain	ch2:Active H	yes	NO	zcn Reset
Operating Ambient Temperature Min. [deg.C]		Operating Ambient Temperature Max. [deg.C]		Hysteresis voltage Typ. [V]
-40		105		0.1~4.0
Additional function				
Separated Sense pin				

## Package

SOT-26B

## Latest News

2023.09.26

[\[Engineering Information\] "What is a shunt regulator?" is available now](#)

2023.07.03

[\[Engineering Information\] "What is RESET IC?" is available now](#)[All News](#)

## Case Studies

ミネベアミツミ株式会社

Copyright©MinebeaMitsumi Inc. All right reserved.

## PST122D

2024/02/28



**No amplifier or software design required. Development of an LDO for automobiles with open load/short circuit detection function. [Power Supply IC]**