

Overview

This IC is a reset IC for turning on/off power supply and power flicker in CPU or logic systems.  
This IC can change delay time by an external capacitor.

Application

- Reset circuits for microcomputers, CPUs and MPUs
- Reset circuits for logic circuits
- Battery voltage check circuits
- Back-up power supply switching circuits
- Level detection circuits

Features

Low current consumption,  
Small package

Main specifications

Absolute maximum rating [V]	Recommended operating voltage Min. [V]	Recommended operating voltage Max. [V]	Detection voltage Min. [V]	Detection voltage Max. [V]	Detection voltage accuracy [%]	Consumption current [μA]
7.0	0.95	6.50	1.2	5.2	±1	0.35
Release delay time	Output type	Output Logic	Separated sense pin	Manual reset	Circuit structure	
Adjustable	CMOS	Active L	No	No	1ch Reset	

Operating Ambient Temperature Min. [deg.C]	Operating Ambient Temperature Max. [deg.C]	Hysteresis voltage Typ. [V]	Delay resistance Typ. [M OHM]
-40	105	VTH(Typ.)×0.05	10
Detection pin threshold voltage Typ. VDD×0.5			

Package

PLP-4C

Latest News

- 2023.09.26

[Engineering Information] "What is a shunt regulator?" is available now
- 2023.07.03

[Engineering Information] "What is RESET IC?" is available now

All News

Case Studies

## PST89DA

2024/02/28



**No amplifier or software design required. Development of an LDO for automobiles with open load/short circuit detection function. [Power Supply IC]**